

Scanner Datalogic Quickscan QD 2430

Konfiguration Datalogic Quickscan QD 2430 Barcode Scanner für Futura4POS

Angelegt von Jan Schinacher, zuletzt geändert am 22.11.2016

Konfiguration Scanner

Pos.	Barcode	Information
1	 Restore EU Factory Configuration	Restore EU Factory Configuration
2	- WARTEN BIS RESET ERLEDIGT -	
3	 Select USB Keyboard	USB Keyboard Mode
4	- WARTEN BIS ERLEDIGT -	
5	 Enter/Exit Programming Mode	Enter Configuration
6	 Label ID Pre-loaded Set = EU Set	Code Identifier Datalogic Standard
7	 Label ID Transmission = Enable as Prefix	
8	 Enter/Exit Programming Mode	Exit and Save Configuration

Datalogic QuickScan QD 2430



Pos.	Barcode	Information
9	- WARTEN BIS ERLEDIGT -	
10	 Enter/Exit Programming Mode	Enter Configuration
11	 Set Global Prefix	Set Global Prefix
12	 0	0
13	 2	2
14	 3	3
15	 4	4
16	 Enter/Exit Programming Mode	Save Configuration

Pos.	Barcode	Information
17	 Enter/Exit Programming Mode	Exit Configuration
18	- WARTEN BIS ERLEDIGT -	
19	 Enter/Exit Programming Mode	Enter Configuration
20	 Set Global Suffix	Set Global Suffix
21	 0	0
22	 A	A
23	 Enter/Exit Programming Mode	Save Configuration
24	 Enter/Exit Programming Mode	Exit Configuration
25	- WARTEN BIS ERLEDIGT -	

Pos.	Barcode	Information
26	 Enter/Exit Programming Mode	Enter Configuration
27	 M20190_01	Keyboard NationalitySchweiz DE
28	 I 2 of 5 = Enable	Enable I 2 of 5
29	 Enter/Exit Programming Mode	Save Configuration
30	- WARTEN BIS ERLEDIGT -	

Test Scanner

Pos.	Barcode	Erwartete Ausgabe im Editor/Notepad
1	 2 900020 070008	4B2900020070008
2	 730000001560000016500000150	4T730000001560000016500000150
3	 0 75380 05606 0	4C075380056060
4	 4008 4329	4A40084329

Pos.	Barcode	Erwartete Ausgabe im Editor/Notepad
5	 1234567890	4N1234567890

Datalogic Konfigurations-Handbuch

Datei: 820055914.pdf



Keine Stichwörter

Revision #1

Created 2024-02-21 10:00:49 UTC

Updated 2024-04-02 08:55:16 UTC